



Generators
PETROL GENERATORS

Petrol Generator GSEm 3002 SB

GSEm 3002 is Petrol Generator, with output max power of 3.0kW, 230V, light and portable generator, easy to start, durable with 10 hours working time.

Advantages:

- EURO 5 engine
- Heavy-duty, strong frame
- Manual start
- AVR System
- Big fuel tank
- Control panel with two 230V/16A AC sockets
- 12 V/DC output
- Circuit breaker Control

Technical data:

Max Power	3000 W
Rate Power	2800 W
Dual Power	No
Voltage	230 V
Socket	2x230Vx16A
ATS Connector	No
Voltmeter	Digital display
Over Voltage Protector	Yes
Displacement	208 cc
Start System	Manual
Fuel Capacity	15 l
Run time 75% load	10 hr
LPG	No
Dimensions (LxWxH)	605x445x450 mm
Weight	45 kg

